

DPA 503N

3-PHASE DIGITAL POWER ANALYZER FOR HARMONICS & FLICKER TESTING



FOR TESTS ACCORDING TO ...

- > EN 301489-1
- > EN 301489-17
- > EN 301489-24
- > EN 301489-7
- > EN 61000-3-11
- > EN 61000-3-12
- > EN 61000-3-2
- > EN 61000-3-3
- > EN 61000-4-15
- > EN 61000-4-7
- > EN 61000-6-1
- > EN 61000-6-2
- > IEC 60601-1-2
- > IEC 61000-3-11
- > IEC 61000-3-12 Ed.2:2011
- > IEC 61000-3-2
- > IEC 61000-3-3
- > IEC 61000-4-15 Ed.2:2010
- > IEC 61000-4-7
- > IEC 61326
- > JIS C 61000-3-2

DPA 503N - FULL-COMPLIANT 3-PHASE HARMONICS AND FLICKER ANALYZER

Harmonics and interharmonics are caused by modern electronic power conditioning modules. Such, mostly non-linear, modules to control loads and to reduce power consumption is the source of voltage at unwanted frequencies superposed on the supply voltage.

Voltage fluctuations caused by varying load currents may influence luminance or spectral distribution of lighting systems. The impression of unsteadies of visual sensation induced by this light stimulus is called flicker.

The DPA 503N is used for 3-phase applications but also supports single phase applications.

HIGHLIGHTS

- > Real-time data acquisition
- > Internal hard disk for data storage
- > 16-Bit A/D converter
- > 6 input channels
- > Wide-range current input up to 140Arms
- > Wide-range voltage input up to 530Vrms
- > High-sophisticated analyzing capability

APPLICATION AREAS

- | | | | |
|---|-------------|---|------------------|
|  | INDUSTRY |  | TELECOM |
|  | MEDICAL |  | RENEWABLE ENERGY |
|  | BROADCAST | | |
|  | RESIDENTIAL | | |

TECHNICAL DETAILS

MEASURING SYSTEM		HARMONICS ANALYSIS																											
Input channels	6 (3x current & 3x voltage)	As per	IEC/EN 61000-3-2 Ed.3 JIS C 61000-3-2 (2013) IEC/EN 61000-3-12:2011																										
Frequency range	15Hz - 3,000Hz	Design as per	IEC/EN 61000-4-7 Ed.2.1 (2009) and IEC/EN 61000-4-7 Ed.1 (1991)																										
A/D converter	16 Bit	Harmonics	1st - 50th order																										
Controller	Embedded processor Pentium 200MHz	Grouping as per	IEC/EN 61000-4-7 (2009) for Interharmonics																										
Signal processor	Motorola DSP	Synchronization	PLL; accuracy better than 0.005%																										
Memory	Internal hard disk	Measuring window	Rectangular window (8,10,12,16 periods)																										
Category	Class I per IEC/EN 61000-4-7	Algorithm	FFT																										
VOLTAGE INPUT		Smoothing filter	1st order 1,5s digital low pass filter (on/off), selectable																										
Input range	10 - 530V rms	Anti-aliasing filter	> 90dB																										
Overload	4,000V peak	Measurement duration	More than 30 hours, limited by the hard-disk capability (approx. 1MB/min of measuring data)																										
Accuracy	Better than 0.4% of reading	Display	Vrms, Irms, Ipeak, Vpeak																										
CURRENT INPUT		Harmonics	V, I, Phase, P, Q, S (2nd - 50th order)																										
Input range	Depending on used CT model. Max. 140A with delivered CT model	Power information	P, Q, S, Power factor, THD(U), THD(I), Crest factor(u), Crest factor(i)																										
Accuracy external CT	Related to 16A 2 turns better than 0.8% 5 turns better than 0.6%																												
GENERAL DATA																													
Temperature	0°C - 40°C	FLICKER ANALYSIS																											
Rel. humidity	10% - 90%, non-condensing	Power supply	85V - 255V, 47Hz - 63Hz	As per	IEC/EN 61000-3-3 Ed.3 (2013) IEC/EN 61000-3-11	Power	Max. 50W	Design as per	IEC/EN 61000-4-15 (2010) 230V, 50/60Hz and 120V, 50/60Hz	Dimension	19" 3HU: 133mm x 449mm x 400mm	Accuracy Pst and Plt	Better than 5%	Weight	12kg	Accuracy dmax, dc, dt	0.15%	Insulation	Input to case / input 3kV rms	Flicker data	Pst and Plt, Vrms, dmax, dc, dt, P50%S, P10%S, P3%S, P1%S, P0.1%	Interface	USB for control and data transfer	Maximum values	Pst, dmax, dc, dt			Observation period	Min. 1min, selectable
Power supply	85V - 255V, 47Hz - 63Hz	As per	IEC/EN 61000-3-3 Ed.3 (2013) IEC/EN 61000-3-11																										
Power	Max. 50W	Design as per	IEC/EN 61000-4-15 (2010) 230V, 50/60Hz and 120V, 50/60Hz																										
Dimension	19" 3HU: 133mm x 449mm x 400mm	Accuracy Pst and Plt	Better than 5%																										
Weight	12kg	Accuracy dmax, dc, dt	0.15%																										
Insulation	Input to case / input 3kV rms	Flicker data	Pst and Plt, Vrms, dmax, dc, dt, P50%S, P10%S, P3%S, P1%S, P0.1%																										
Interface	USB for control and data transfer	Maximum values	Pst, dmax, dc, dt																										
		Observation period	Min. 1min, selectable																										

TECHNICAL DETAILS

OPTIONS

FLICKER IMPEDANCE AIF 503NX (OPTION; SEPARATE UNIT)	
Models	AIF 503N16 (16 A) AIF 503N32.1 (32 A) AIF 503N63.1 (63 A) AIF 504N75.1 (75 A)
As per	IEC/EN 61000-3-3, IEC/EN 61000-3-11 and IEC 60725 for 3-phase applications
Zref	all models
Line L1, L2, L3	0.24ohm + j0.15ohm
Neutral	0.16ohm + j0.10ohm
Ztest	excluding model AIF 503N16
Line L1, L2, L3	0.15ohm + j0.15ohm
Neutral	0.10ohm + j 0.10ohm
Accuracy	Better than 3%
R.M.S. current	Depending on selected model
	Each inductor is designed as a non-saturable air coil and is matched manually to the specified value.

OUTPUT FOR VERY LOW CURRENT (AIF 503N OPTION)	
VLCM Kit AIF 503N	
Measuring output	Separate output for very low current on phase L1
Current range	5mA - 500mA
Accuracy	< 1 % of measured value

COMPETENCE WHEREVER YOU ARE



CONTACT EM TEST DIRECTLY

Switzerland

EM TEST (Switzerland) GmbH > Sternenhofstraße 15 > 4153 Reinach > Switzerland
 Phone +41 (0)61/7179191 > Fax +41 (0)61/7179199
 Internet: www.emtest.ch > E-mail: sales.emtest@ametek.com

Germany

AMETEK CTS Germany GmbH > Lünener Straße 211 > 59174 Kamen > Deutschland
 Phone +49 (0)2307/26070-0 > Fax +49 (0)2307/17050
 Internet: www.emtest.com > E-mail: info.cts@ametek.de

France

EM TEST FRANCE > Le Trident - Parc des Collines > Immeuble B1 - Etagé 3 > 36, rue Paul Cézanne > 68200 Mulhouse > France
 Phone +33 (0)389 31 23 50 > Fax +33 (0)389 31 23 55
 Internet: www.emtest.fr > E-mail: info@emtest.fr

Poland

EM TEST Polska > ul. Ogrodowa 31/35, 00-893 Warszawa > Polska
 Phone +48 (0)518 64 35 12
 Internet: www.emtest.com/pl > E-mail: infopolska.emtest@ametek.com

USA / Canada

AMETEK Compliance Test Solutions > 52 Mayfield Ave. > Edison > NJ 08837
 Phone +1 (732) 417-0501
 Internet: www.emtest.com > E-mail: sales.emtest@ametek.com

P.R. China

E & S Test Technology Limited > Rm 913, Leftbank >
 No. 68 Bei Si Huan Xi Lu > Haidian District > Beijing 100080 > P.R. China
 Phone +86 (0)10 82 67 60 27 > Fax +86 (0)10 82 67 62 38
 Internet: www.emtest.com > E-mail: info@emtest.com.cn

Republic of Korea

EM TEST Korea Limited > #405 > WooYeon Plaza > #986-8 > YoungDeok-dong >
 Giheung-gu > Yongin-si > Gyeonggi-do > Korea
 Phone +82 (31) 216 8616 > Fax +82 (31) 216 8616
 Internet: www.emtest.co.kr > E-mail: sales@emtest.co.kr

Information about scope of delivery, visual design and technical data correspond with the state of development at time of release. Subject to change without further notice.